
Tabbed Brackets - For 1 Slot


For 5 Series (Slot Width 6mm) Aluminum Extrusions







otou by boar E and					
Туре	M Material	Surface Treatment			
①HBLFSNF5					
②HBLFSN5	ADC12	-			
③HBLFSN5-4					
4)HBLFSNB5		Black Anodize Electroless Nickel Plating			
5HBLFSNM5					
6CHBLFSN5	1	Baked Paint (Silver)			
*Baked Paint (Silver) is color coordinated with Clear					



Part Number	Mass	Applicable Screw, T Nut				Allowable	Unit Price	Volume Discount Rate
Type	(g)	Screw	Quantity	T Nut	Quantity	Load (N)	1~99 pc(s).	100~200
HBLFSNF5	13	CBM5-10		HNTT5-5				
HBLFSN5		CRINID-10	2	питто-о		1176		
HBLFSN5-4		CBM4-10		HNTT5-4				
(For M4 Screw)				1111113-4				
HBLFSNB5*		CBM5-10		HNTT5-5	2			
(Black Anodize)	15							
HBLFSNM5	0							
(Electroless Nickel Plating)								
CHBLFSN5								
(Baked Paint, Silver)								

* For repairing black anodizing, refer to P.846.



Use one of the two holes on bottom, depending on mounting direction. *Cross-Connection is not available

brackets from protruding from extrusions when

* Ø4.2 for HBLFSN5-4.






M5

(When specifying

alteration C)



Features: One-Sided Tabbed Rib Brackets. Easy to work with wrenches.




Part Number Mass Applicable Screv
Type (g) Screw Quantity T

CBM5-10

13

Type (g)


HBLESL



	HBLFSL5				1		-		
	Ī	HBLFSLB5] A	ADC12		Cathodic Electrodepositio		
	1	HBL	FSLM5	٦_			Electrole	ess Nick	
	-								
crew, T Nut		t	Allowable	Unit	Price	Volur	ne Discount Rate		
T Nut		Quantity	Load (N)	1~99	pc(s).	10	00~200		
						П			
HNTT5-5	;	2	1176						



Can be combined with both cover plates of 5mm and 3mm



28


Features: Pressing nuts against the long tabs makes cumbersome hole positioning unnecessary.





Slotted holes are for various nut hole positions.
PBracket tabs may be damaged when
nuts are fallen on them.
Tuse of washers are recommended.

(Refer to alterations on the next page: Material: ADC12













Features: Brackets with single side tabs. Panels can be mounted on the side without tabs as shown in the app. example



| Part Number | Mass | Applicable Screw, T Nut | Allowable Unit Price | Number | Screw | Ouestify | T Nut | Ouestify | Load (N) | 1-99 pc(s). 100-200 CBM5-10 2 HNTT5-5 2 1176 15


Features: Tabbed Reversal Brackets with Cover. Designed to prevent dust build-up.



Part Number Mass Applicable Screw, T Nut Allowable Unit Price Volume Discount Robe
 Type
 (g)
 Screw
 loadly
 T Nut
 load (N)
 1-99 pc(s)
 100-200

 HBLFSNT5
 17
 CBM5-10
 2
 HNTT5-5
 2
 1176

Features: Tabbed Reversal Brackets with two mounting holes on one side can connect extrusions more securely.




Part Number CBM5-10 HNTT5-5 4 1470

* For repairing black anodizing, refer to P.846



Alterations Code Applicable Bracket Spec. Adds taps on a bracket for Mounting Hole (M5 on Both Sides) for Cove (Mounting Screw HCBM on P.754)

Part Number - (C, SET, SST, SEU, SSU, SEP, SSP, SEC)



Alterations Co	Spe	tions			Applicable Bracket
Applicable Screws and Nuts Set Instru	El (Ex.) When HBLFSN5 Code Screw SET CBM5-10 SST SCB5-10 SEU CBM5-10 SSU SCB5-10 SSP SSP SCB5-10 SSP SSP SCB5-10 SEC HCBST5-12 When specifying o HBLFSN5, check fr screws and nuts.	cable is and set	sions comet price.) specified: Nut HNTT5-5 HNTTBS5 HNTU5-5 SHNTU5-5 SHNTP5-5 HNTT5-5 er than	e in a -	HBLFSNF5 HBLFSN5 HBLFSN5-4 HBLFSN5 HBLFSN5 CHBLFSN5 HBLFSL5 HBLFSL5 HBLFSL5 HBLFSL5 HBLFSN5 HBLFSN5 HBLFSN5 HBLFSN5 HBLFSN5 HBLFSN5 HBLFSN5

Screws for Black Anodized Brackets and Cathodic Electrodeposition Painted (black) Brackets are HCBMTB (Trivalent Chromate Black) on P751.

· Can be mounted on a plate directly.

Example of HBLFSNK5

Example of HBLFSNE5

FS5-2020

Can be connected in narallel and

HFS5-4040