

Strut Clamps

Square & Round / Square & Square, Perpendicular Configuration

■ Features: Post clamps that height adjusts while preventing rotations by combining with Square tubes (P.2159) and Stand Brackets (P.2160). Combined with Stand-Up Brackets, Strut Clamps can prevent rotation while adjusting height. For tubes / pipes and rods usable in sets, see P.2159.

■ Square & Round, Perpendicular Configuration




■ Square & Square, Perpendicular Configuration




Type	Material	Surface Treatment	Accessory
BLQD, NLQD, ALQD, HLQD, SLQD	S45C	Black Oxide	Hex Socket Head Cap Screw
BLQQD, NLQQD, ALQQD, HLQQD, SLQQD	A6063	Electroless Nickel Plating	
	A6063	Black Anodize	
	SUS304	Clear Anodize	

⚠ Accessory: CB screws (P.2-171) are included with black oxide/black anodized products, and SCB screws (P.2-173) are included with the other products, respectively.

Square & Round, Perpendicular Configuration



Square & Square, Perpendicular Configuration




⚠ When D=10 or 12, there is no S dimension. There is only 1 screw at the center for tightening.

Part Number	Type	D _{D8}	D _{1H7}	A	B	C	E	F	H	S	M (Coarse)	d	W
Square & Round, Perpendicular Configuration BLQD, NLQD, ALQD, HLQD, SLQD	Square & Square, Perpendicular Configuration BLQQD, NLQQD, ALQQD, HLQQD, SLQQD	10	10	45	16	16	15	15	9	-	M5	5.5	2
		12	12	49	16	16	16	17	10	-	M5	5.5	
		15	15	57	22	22	18	21	12	11	M5	5.5	
		20	20	69	28	28	22	25	15	14	M6	6.6	
		25	25	83	32	32	25	33	18	16	M6	6.6	

⚠ The tolerance and perpendicularity of D_{D8} and D_{1H7} are the tolerances before slitting.
⚠ Recommended D_{D8} tolerance of mating shafts is 0 - -0.12 and D_{1H7} tolerance g6 and g8 respectively. Tightening with a long wrench is recommended.

Ordering Example
Part Number
ALQD20
SLQQD10

EX Example



D	Unit Price									
	Square & Round, Perpendicular Configuration			Square & Square, Perpendicular Configuration						
	S45C	A6063	SUS304	S45C	A6063	SUS304				
	BLQD	NLQD	ALQD	HLQD	SLQD	BLQQD	NLQQD	ALQQD	HLQQD	SLQQD
10										
12										
15										
20										
25										

Strut Clamps

Vertical / Parallel Taps, Square Hole

■ Features: Post clamps that height adjusts while preventing rotations by combining with Square tubes (P.2159) and Stand Brackets (P.2160). For tubes/pipes and rods usable in sets, see P.2159.


■ Vertical Taps, Square Hole




Type	Material	Surface Treatment	Accessory
BMNQ, NMNQ, AMNQ, WMNQ, SMNQ	S45C	Black Oxide	Hex Socket Head Cap Screw
BQMQ, NQMQ, AQMQ, WQMQ, SQMQ	A6063	Electroless Nickel Plating	
	A6063	Black Anodize	
	SUS304	Clear Anodize	

⚠ Accessory: CB screws (P.2-171) are included with black oxide/black anodized products, and SCB screws (P.2-173) are included with the other products, respectively.

Vertical Taps, Square Hole



Parallel Taps, Square Hole



⚠ When D=10 or 12, there is no S dimension. There is only 1 screw at the center for tightening.

■ Vertical Taps, Square Hole

Part Number	Type	D _{D8}	P	A	B	C	E	G	H	S ₁	M ₁	S	M	d	Unit Price				
															BMNQ	NMNQ	AMNQ	WMNQ	SMNQ
BMNQ, NMNQ, AMNQ, WMNQ, SMNQ	Vertical Taps, Square Hole	10	11	31	16	16	15	5	9	8	M4	-	M5	5.5					
		12	13	34	16	16	16	5	10	8	M4	-	M5	5.5					
		15	17	45	22	22	20	8	12	12	M5	12	M6	6.6					
		20	20	52	28	28	22	10	15	16	M6	14	M6	6.6					
		25	23	58	32	32	25	10	18	20	M6	16	M6	6.6					

⚠ Tolerance of D_{D8} is the tolerance before slitting.
⚠ Recommended D_{D8} tolerance of mating shafts is 0 - -0.12. Tightening with a long wrench is recommended.

■ Parallel Taps, Square Hole

Part Number	Type	D _{D8}	P	A	B	C	E	H	S ₁	M ₁	S	M	d	Unit Price				
														BQMQ	NQMQ	AQMQ	WQMQ	SQMQ
BQMQ, NQMQ, AQMQ, WQMQ, SQMQ	Parallel Taps, Square Hole	10	16	31	16	16	15	9	8	M4	-	M5	5.5					
		12	18	34	16	16	16	10	8	M4	-	M5	5.5					
		15	25	45	22	22	20	12	12	M5	12	M6	6.6					
		20	30	52	28	28	22	15	16	M6	14	M6	6.6					
		25	33	58	32	32	25	18	20	M6	16	M6	6.6					

⚠ Tolerance of D_{D8} is the tolerance before slitting.
⚠ Recommended D_{D8} tolerance of mating shafts is 0 - -0.12. Tightening with a long wrench is recommended.

Ordering Example
Part Number
AMNQ15
SQMQ20

EX Example

